

Three Phase Inverters for Residential Installations for Australia

SE5K-AU / SE7K-AU / SE8K-AU

INVERTERS



Specifically designed to work with power optimisers

- // Noise level suitable for residential environment – No external fan
- // Quick and easy inverter commissioning directly from a smartphone using the SolarEdge SetApp
- // Superior efficiency (98%)
- // Small, lightest in its class, and easy to install
- // Built-in module-level monitoring
- // Internet connection through Ethernet or Wireless (via Wi-Fi or Cellular plug-ins)
- // Integrated DC Safety Unit - Eliminates the need for external DC isolators
- // IP65 – Outdoor and indoor installation
- // Fixed voltage inverter for longer strings

/ Three Phase Inverters for Residential Installations for Australia

SE5K-AU / SE7K-AU / SE8K-AU

SE5K-AU		SE7K-AU		SE8K-AU	
APPLICABLE TO INVERTERS WITH PART NUMBER		SEXK- AUXTXBNU4			
OUTPUT					
Rated AC Power Output	4985	7000	8000	W	
Maximum AC Power Output	4985	7000	8000	VA	
AC Output Voltage - Line to Line / Line to Neutral (Nominal)	380 / 220				Vac
AC Output Voltage - Line to Neutral Range	184 - 264.5				Vac
AC Frequency	50/60 ± 5%				Hz
Maximum Continuous Output Current (per Phase)	8	11.5	13	A	
Grids Supported - Three Phase	3 / N / PE (WYE with Neutral)				
Utility Monitoring, Islanding Protection, Configurable Power Factor, Country Configurable Thresholds	Yes				
INPUT					
Maximum DC Power (Module STC)	6750	9450	10800	W	
Transformer-less, Ungrounded	Yes				
Maximum Array Input Voltage	600				Vdc
Maximum Voltage to Earth (DC to GND)	415				Vdc
Maximum Input Current	8.5	12	13.5	Adc	
Reverse-Polarity Protection	Yes				
Ground-Fault Isolation Detection	700kΩ Sensitivity				
Maximum Inverter Efficiency	98				%
European Weighted Efficiency	97.3	97.4	97.6	%	
Nighttime Power Consumption	< 2.5				W
ADDITIONAL FEATURES					
Supported Communication Interfaces ⁽¹⁾	RS485, Ethernet, Wi-Fi ⁽²⁾ , ZigBee for Smart Energy (optional) ⁽³⁾ , Cellular (optional)				
Inverter Commissioning	With the SetApp mobile application using built-in Wi-Fi access point for local connection				
Smart Energy Management ⁽⁴⁾	Export Limitation, Home Energy Management (Device Control)				
STANDARD COMPLIANCE					
Safety	IEC62109, AS/NZS3100				
Grid Connection Standards	AS/NZS4777:2015				
Emissions	IEC61000-6-2, IEC61000-6-3 , IEC61000-3-11, IEC61000-3-12, FCC part15 class B				
RoHS	Yes				
INSTALLATION SPECIFICATIONS					
AC output conduit size / Wire cross section	20mm minimum / 3-13mm²				
DC input conduit size / Wire cross section	20mm minimum / 3-13mm²				
DC Input	Terminal blocks for 2 arrays enclosed through 2 separate conduits ⁽⁵⁾				
Dimensions with Safety Switch (H x W x D)	775 x 315 x 191				mm
Weight	22.2				kg
Operating Temperature Range	-40 - +60 ⁽⁶⁾				°C
Cooling	Internal fan				
Noise	< 40				dBA
Protection Rating	IP65 - Outdoor and Indoor				
Mounting	Bracket Provided				

(1) Refer to Datasheets -> Communications category in Downloads page for specifications of optional communication options: <http://www.solaredge.com/groups/support/downloads>

(2) Wi-Fi connectivity requires an external antenna. For more information refer to: <http://www.solaredge.com/sites/default/files/se-wifi-zigbee-antenna-datasheet.pdf>

(3) For more information refer to: <https://www.solaredge.com/sites/default/files/se-zigbee-plug-in-wireless-communication-for-setapp-datasheet-au.pdf>

(4) An export meter is required for export limitation and most of home energy management functions

(5) Two arrays must be connected to the inverter; refer to image below. For complete design guidelines refer to:

https://www.solaredge.com/sites/default/files/three_phase_inverter_residential_design_installation_addendum_aus.pdf

(6) For power de-rating information refer to: <https://www.solaredge.com/sites/default/files/se-temperature-derating-note.pdf>

/ Three Phase Inverters for Residential Installations for Australia

SE5K-AU / SE7K-AU / SE8K-AU

