

RENOGY 1000W 12V PURE SINE WAVE INVERTER

Input Voltage: 12VDC

Continuous Power: 1000W

Surge Power: 2000W

Output Voltage: 220VAC±10

Output Frequency (Nominal): 50Hz±0.3

Output Wave form:Pure Sine Wave

No Load Current Draw: < 1A

Input Voltage Range: 11-16Vdc

Low Voltage Shutdown: 10Vdc

Recover from low voltage protection

Battery supply & AC main transfer time within 50ms

Efficiency: > 90%

Dimensions: 34.2 x 17.3 x 7.6 cm

Weight: 2.6Kg

Certifications:

CE

YES

EMC

YES