RENOGY	2000W 12V	PURE SINE V	VAVE INVERT	ER

Input Voltage: 12VDC

Surge Power: 4000W

Static Current: 1.3A

Output Frequency (Nominal): 50Hz±0.3

Low Voltage Shutdown: 10Vdc

Dimensions: 442*220*92 mm Certifications:

Battery supply & AC main transfer time within 50mS

Continuous Power: 2000W

Output Voltage: 220VAC±10

Output Wave form:Pure Sine Wave

Recover from low voltage protection

High Voltage Shutdown: 16.3Vdc

Weight: 4.8Kg

YES

YES

Input Voltage Range: 11-16Vdc

CE EMC